

TECHNICAL DATA

Fluke 9040 Phase Rotation Indicator



Key features

- 3 phase indication
- Indication of phase rotation
- Clear LCD display
- No battery required

Product overview: Fluke 9040 Phase Rotation Indicator

Phase rotation indicator with high voltage capability for industrial applications

The Fluke 9040 is effective for measuring phase rotation in all areas where three phase supplies are used to feed motors, drives and electrical systems. The Fluke 9040 is a rotary field indicator and can provide clear indication of the 3 phase via an LCD display and the phase rotation direction to determine correct connections. It allows rapid determination of phase sequence and has a voltage (up to 700 V) and frequency range suitable for commercial and industrial applications. The included test probes have a variable clamping range for safe contact, also in industrial sockets.

Specifications: Fluke 9040 Phase Rotation Indicator

| Technical Specifications | |
|--------------------------|-----------|
| Voltage Range | 40-700 V |
| Frequency Range | 15-400 Hz |

| | |
|--|----------------------|
| Operating Timer | Continuous |
| Environmental Specifications | |
| Operating Temperature | 0°C to 40°C |
| Dust/Water Resistance | IP 40 |
| Safety Specifications | |
| Electrical Safety | EN 61010, |
| | EN 61557-7 |
| Overvoltage category | CAT III, 600 V |
| | CAT IV, 300V |
| Mechanical and General Specifications | |
| Size | 124 x 61 x 27 mm |
| Weight | 200 g |
| Power supply | From unit under test |
| Warranty | 2 years |

Ordering information



Fluke 9040

Fluke 9040 Phase Rotation Indicator

Includes:

- 3 self-retaining test probes (black)
- alligator clip
- user manual

Fluke. *Keeping your world up and running.®*

Fluke Europe B.V.
P.O. Box 1186
5602 BD Eindhoven
The Netherlands
www.fluke.com/en

©2023 Fluke Corporation. All rights reserved.
Data subject to alteration without notice.
07/2023

For more information call:
In Middle East/Africa
+31 (0)40 267 5100

**Modification of this document is not permitted
without written permission from Fluke Corporation.**