

## TECHNICAL DATA

# Fluke 80K-15 High Voltage Probe



## Key features

- **Voltage range:** 0 to 15kV DC or peak AC, 10kV rms AC
- **Basic accuracy:** DC +/- 2% 60Hz: +/- 5%
- **Division ratio:** 1000:1
- **Safety standards:** IEC 1010-2-031:1993, Type B, 40 kV DC or peak AC, 28kV rms AC, Overvoltage Category I (voltage derived from limited energy transformer).
- **Input resistance:** 1000 Megohm
- **Required meter input resistance:** 10 Megohm

## Product overview: Fluke 80K-15 High Voltage Probe

The 80K-15 is a high voltage probe designed to extend the voltage measuring capability of an AC/DC voltmeter to 15,000 volts peak AC or DC Overvoltage Category I. This means the probe can only be used to make measurements on energy limited circuits within equipment. Examples include high voltage within televisions or photocopy machines. DO NOT use this probe to measure high voltages on power distribution systems. The probe provides high accuracy when used with a voltmeter having 10 Megohm input impedance.

## Ordering information



**Fluke 80k 15**

**Fluke.** *Keeping your world up and running.®*

**Fluke Europe B.V.**  
P.O. Box 1186  
5602 BD Eindhoven  
The Netherlands  
[www.fluke.com/en](http://www.fluke.com/en)

©2023 Fluke Corporation. All rights reserved.  
Data subject to alteration without notice.  
07/2023

**For more information call:**  
In Middle East/Africa  
+31 (0)40 267 5100

**Modification of this document is not permitted  
without written permission from Fluke Corporation.**